

Warnings

CAUTION—risk of fire and this product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.

Suitable for wet locations.

Mounting orientation must have light source facing down.

Electrical service must be disconnected during installation.

Proper grounding is required to protect against shock and proper operation.

Tools Required

- 7/64" Allen wrench
- Phillips head screw driver
- Wiring tools and connectors

Installation

Step 1: Turn off power to location.

Step 2: Screw supplied rigid stem onto 1/4" IPS nipple on top of luminaire.

Step 3: Slide junction box cover onto rigid stem. Screw junction box mounting plate onto rigid stem and secure with pipe supplied pipe nut. Mounting only fits on a 4" octagonal junction box (supplied by others) with opening flush to ceiling surface.

Step 4: Make wire connection inside junction box.

Step 5: Secure junction box mounting to junction box using screws supplied with junction box. Slide junction box cover up until held by magnets attached to mounting plate.

Step 6: Turn power back on to location.

